



1. Download and install Live Updates from Stellar Support

- Go to www.stellarsupport.com
- Select English, next to USA
- Click on Software Updates
- Click on Greenstar 3 2630 & Greenstar 2 Displays and Controllers
- Click on yellow Download Now button
- Open the Live Update installer and follow the steps
 - Select Next on the Country and Language Page
 - Select the 2630 Box on the Greenstar Display Page, then press Next
 - Press next again to download the updates
 - Agree to the License Agreement, then press next
 - Wait for the Download to complete, then press Next (creating a shortcut to GSLive Update will make it easier to download future updates)

2. Copy the updates to a USB Drive

- Once GS Live Update is installed, it will automatically open
- Press the Next button to verify you have the latest updates
- Install a blank USB Drive
 - Drive must be 16GB or smaller
 - Format as Fat32 if formatting a new drive
- Press Copy to start the process to put the update on the USB Drive
- Select your Display model of 2630
- Press Next to begin copying to the USB Drive
- Press Close when Complete

3. Install Updates via the 2630 Display

- Note: It is best to unplug any Rate Controllers when doing this update to prevent any issues
- Power on the 2630 Screen
- Once booted up, insert the USB on the right side of the display
- From the Pop-Up, choose Install Software
- Review the list of available updates, then press Install